



- ST890D Digital Multi-Meter



Product No.: ST890D

SPECIFICATIONS

DC Voltage DCV	200mV/2V/20V/200V/1000V
AC Voltage ACV	2V/20V/200V/750V $\pm(0.5\%+5)$
Resistor	200 Ω /2k Ω /20k Ω /200k Ω /2M Ω /20M $\Omega \pm(0.8\%+3)$
Diode	20nF/200nF/2uF/20uF/200uF/2mF/20mF $\pm(2.0\%+30)$
AC Current	20mA/200mA/10A $\pm(1.5\%+10)$
DC Current	20uA/2mA/20mA/200mA/10A $\pm(1.5\%+10)$
Buzzer/Diode Measurement	✓
NVC Test	✓
Backlight function	✓
Manual/Auto Power off	✓
Hold function	✓